



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A245	-	1/15	208-230	3000/1	CW	0.95/0.85	-	-	-
3.3 inch, Shaded pole, ball bearing									
Replaces: 7021-7490, 70-42278-02									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A246	-	1/20	115	3400/2400/2	CW	0.85	-	-	-
3.3 inch, PSC, ball bearing									
Replaces: 7062-3925, 70-24206-01									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A247	-	1/40	115	3250/ 2800/2	CW	0.95	-	-	-
3.3 inch, PSC, sleeve bearing									
Replaces: 7062-5519									
									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
D724	-	3/4 - 1/2 - 1/3 - 1/4	115	1075/4	REV	9.5 - 7.2 - 5.6 - 3.5	6.00	5.75	-
5.6 inch, PSC, sleeve bearing, 15@370V capacitor required (MARS # 12010), includes 8 drilled and tapped holes in shell									
Replaces: VARIOUS									
							FASCO		



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
10463	-	1/2 - 1/3 - 1/4 - 1/6	115	1075/4	REV	6.2	5.50	4.73	0.50
5.5 inch dia., open endshields, sleeve bearing, capacitor required noted on motor label, direct drive blower motor									
Replaces: 51-23012-41									
									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
D2840	-	1/5	208/230	1075/1	CW	1.3	4.13	3.75	0.50
5.6 inch, PSC, sleeve bearing, 4 drilled and tapped holes in shell									
Replaces: 51-21853-82									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
D2842	-	1/6	208/230	825/1	CW	1.2	4.25	4.00	0.50
5.6 inch, PSC, sleeve bearing, 4 drilled and tapped holes in shell									
Replaces: 51-20760-11									
									




Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
D832	-	1/8	208 - 230	825/1	REV	1.1	4.75	4.00	0.50
3.3 inch, PSC, sleeve bearing, 4 drilled and tapped holes in shell									
Replaces: 21276-02, 21276-01, 512076-01									
FASCO									




Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
D459	-	1/15	230 / 460	3000/1	CW	1.2-0.60	3.00	7.00	0.25
3.3 inch, Shaded pole, ball bearing, 1/4 inch dia. shaft									
Replaces: HC24AU725A, JB1P044, AB1S078, JB1R039, AB1S029, S88-556									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
K628	-	1/200	208 - 230	3000/1	CW	0.25	1.50	4.90	0.25
Shaded pole, sleeve bearing, 1/4 inch dia. shaft									
Replaces: 51-21964-01, 7102-0628									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A079	-	1/50	115	3000/1	CCW	1.1	-	-	-
3.3 inch, Shaded pole, sleeve bearing									
Replaces: 74-70-21504-03-04, 74-70-21496-03-01, JAIM106, JAIM137, 7021-5615									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A086	-	1/25	115	3200/1	CW	1.3	-	-	-
3.3 inch, Shaded pole, sleeve bearing									
Replaces: 7021-5853							FASCO		



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A090	-	1/50	115	3000/1	CW	1.1	-	-	-
3.3 inch, Shaded pole, sleeve bearing									
Replaces: RHEEM 70-21496-01, 7021-5239 JAIM102									



Rheem/Ruud

MARS NO.	MFG. NO.	HP	VOLTS	RPM/ SPD	ROT	AMPS	DIMENSIONS		
							A	B	C
A136	-	1/20	115	3450/1	CW	0.75	-	-	-
3.3 inch, PSC, sleeve bearing 4@370V capacitor required (MARS # 12004)									
Replaces: RHEEM. 7062-3861									
							FASCO		