Enovative® AutoHot

JOB or CUSTOMER:			
ENGINEER:			
CONTRACTOR:			
SUBMITTED BY:	APPROVED BY:	ORDER NO:	
Date:	Date:	Date:	

SUBMITTAL | SPECIFICATIONS

WM-S-16A

(Wireless Motion Sensor)



Description

The wireless motion sensor is used in conjunction with the Wireless Receiver (WR-16A) to activate the AutoHot $^{\circ}$ ondemand system, from anywhere in the home. The range of the motion sensor is up to 500 feet, in open air and up 10 sensors can be used per receiver. May also be used in combination with the AutoHot wireless button sensor (WB-S-16A).

3	Height: 3.375 Inches 2	Depth: .5 Inches	Net Wigh 35 Gran		Width: 2.125 Inches	Gross Wight: 45 Grams
တ	Working Voltage	DC 3V (2 AAA	batteries)	Voltage	under USB line power supply	5V
	Working current	15Ma		Working	frequency	433 MHz ± 2MHz
ΙĒ	Current in suspend mode	30 Ua		Working	temperature	-15°C ~ 60°C
[[Detecting area	4~5Mx110°		Waterpr	oof (Yes or No)	No
SPECIFICATIONS	Working range between reciver and sensor	120~150m in the open air 4 (1 red LED for low power alert, 3 blue LED for detecting alert or ext				
S	LED lights			xtremely low power)		

WB-S-16A (Wireless Button Sensor)



Description

The Wireless Button is used with the Wireless Receiver (WR-16A) to activate the AutoHot ondemand system from a remote location, and has a range of about 1000 feet in open air. Up to 10 wireless buttons can be used per receiver and comes with mounting screws and double-sided foam tape for easy mounting. May be used in combination with the AutoHot wireless motion sensor (WM-S-16A)

2.	Height: 8125 Inches	Depth : .75 Inches		Net Wight: 20 Grams	Width: 1.625 Inches	Gross Wight: 22 Grams	
NO	Transmitter work	ing voltage	AC 1	10V-220V 50Hz/60Hz			
CATI	Transmitter power consumption		0.5	V			
SPECIFICATIO	Transmitter volume		25-1	10db			
SPE	Operating frequency		433	MHz ± 2MHz			

WR-16A (Wireless Receiver)



Description

The Wireless Receiver is used with the AutoHot wireless buttons (WB-S-16A) or Wireless Motion Sensors (WM-S-16A), or a combination of both. Receiver plugs into the AutoHot controller and up to 10 sensors my be used per receiver.

3	Height: 375 Inches	Depth: 1 Inches	Net Wight: 76 Grams	Width: 3.1875 Inches	Gross Wight: 76 Grams		
	Input of receiver		AC 110V / 220V 50Hz/60Hz				
	Optional melodies		52				
ΔŦ	Volume lodness		30-110db				
	Plug type		RJ45 connector				
	Expandable (Yes or No)		Yes				
SPECIFICATION	Work frequency		433 MHz ± 2MHz				
	Working temperat	cure	-15°C ~ 60°C				



Enovative® AutoHot

JOB or CUSTOMER:			
ENGINEER:			
CONTRACTOR:			
SUBMITTED BY:	APPROVED BY:	ORDER NO:	
Date:	Date:	Date:	

Net weight:

SUBMITTAL | SPECIFICATIONS

HB-S-13A


(Hardwired Push Button)

Description

The hardwired push button activator is a normally open, momentary contact switch that signals the AutoHot to turn on when pressed by the user. One hard wired push button comes standard with every AutoHot system and is suitable for a 16mm mounting hole. You can run multiple hardwired buttons in parallel to activate the AutoHot system from various fixture locations.



	Thread diameter: 16 mm	Length: 24 mm / 0.94"
<u>ග</u>	Contact type	Momentary (1NO)
6	Head shape	Hight Round
F	Switch rating	36 VDC, 2A
2	Terminal number	2; Mounting
SPECIFICATIONS	Material	Stainless Steel
	Housing color	Silver Tone, Blue
S	Thread diameter	16 mm / 0.63"



Width:

HM-S-17A [Hardwired Motion Sensor]



	Model	SFL-350
	Detecting Distance	8M
တ	Working Voltage	9-16VDC
B	Detecting Angle	360° LED Light is ON
AT	Working Current	≤ 18mA (DC 12V)
	Working Temperature	-10~50°C
SPECIFICATIONS	Dimension	88mm x 22mm
S	Installation	Ceiling Mounted
	Alarm Output	N.O/N.C (Optional)
ľ	Alarm Sensitivity	Adjustable, suit for different district and temperature
	LED ON/OFF Optional	Suit for any Alarm System

HR-S-17W [Hardwired Rocker Switch-White]



	Part Number	HR-S-17W
	Product Description	15A 277V Single Control Momentary Contact Rocker Toggle Switch
	Size	65mm x 32mm x 38mm
	Max. Current	15A
<u>ග</u>	Max. Voltage	277V
8	Mechanical Life	10 Years
SPECIFICATIONS	Color	White
윤	Material	рс
	Туре	Electronic Switch
명	Feature	Safety
	Function	Touch Panel Light Wall Switch
	Application	House