


Schedule 40 Fittings Technical  
**Schedule 40 Fittings Dimensions & Information**



## Coupling - Reducer

(Continued)

Socket x Socket




| Part Number           | Size  | L       | M        | M1       | N      | Approx. Wt. (Lbs.) |
|-----------------------|-------|---------|----------|----------|--------|--------------------|
| 429-920F <sup>*</sup> | 24X20 | 28- 3/4 | 25- 3/16 | 21- 3/16 | 6- 3/4 | 68.51              |

<sup>1</sup> Outlet sized with Bushing

\* Fabricated

## Coupling - Eccentric Reducer

Socket x Socket



| Part Number             | Size        | L        | M       | M1      | N       | Approx. Wt. (Lbs.) |
|-------------------------|-------------|----------|---------|---------|---------|--------------------|
| 429-131FE <sup>*</sup>  | 1X3/4       | 3-5/8    | 1-9/16  | 1-1/4   | 1-3/8   | .07                |
| 429-168FE <sup>*</sup>  | 1-1/4X1     | 4-3/8    | 1-15/16 | 1-9/16  | 1-5/8   | .11                |
| 429-211FE <sup>*</sup>  | 1-1/2X1     | 5-3/16   | 2-3/16  | 1-9/16  | 2-7/16  | .16                |
| 429-212FE <sup>*</sup>  | 1-1/2X1-1/4 | 4- 5/8   | 2- 3/16 | 1-15/16 | 1- 5/8  | .19                |
| 429-249FE <sup>*</sup>  | 2X1         | 8-3/8    | 2-11/16 | 1-9/16  | 5-3/8   | .38                |
| 429-250FE <sup>*</sup>  | 2X1-1/4     | 5- 3/4   | 2- 5/8  | 1-15/16 | 2- 1/2  | .28                |
| 429-251FE <sup>*</sup>  | 2X1-1/2     | 5-1/8    | 2-11/16 | 2- 3/16 | 1-7/8   | .29                |
| 429-290FE <sup>2*</sup> | 2-1/2X1-1/4 | 9- 5/8   | 3- 3/16 | 1-15/16 | 6- 1/8  | .59                |
| 429-291FE <sup>2*</sup> | 2-1/2X1-1/2 | 9        | 3- 3/16 | 2- 3/16 | 5-1/2   | .59                |
| 429-292FE <sup>*</sup>  | 2-1/2X2     | 6- 3/8   | 3- 3/16 | 2-11/16 | 2- 5/8  | .44                |
| 429-335FE <sup>3*</sup> | 3X1         | 13-3/4   | 3-13/16 | 1-9/16  | 10-1/4  | .94                |
| 429-336FE <sup>2*</sup> | 3X1-1/4     | 11- 1/8  | 3-13/16 | 1-15/16 | 7- 3/8  | .74                |
| 429-337FE <sup>2*</sup> | 3X1-1/2     | 10-1/2   | 3-13/16 | 2- 3/16 | 6-3/4   | .77                |
| 429-338E                | 3X2         | 5- 7/8   | 4- 5/32 | 2- 7/8  | 2-15/32 | 1.00               |
| 429-338FE <sup>*</sup>  | 3X2         | 7-15/16  | 3-13/16 | 2-11/16 | 3-15/16 | .59                |
| 429-339FE <sup>*</sup>  | 3X2-1/2     | 6- 3/4   | 3- 7/8  | 3- 1/4  | 2- 1/2  | .79                |
| 429-417FE <sup>4*</sup> | 4X1         | 18-3/4   | 4-15/16 | 1-9/16  | 15-1/4  | 1.75               |
| 429-418FE <sup>3*</sup> | 4X1-1/4     | 16- 1/8  | 4-15/16 | 1-15/16 | 12- 3/8 | 1.69               |
| 429-419FE <sup>3*</sup> | 4X1-1/2     | 15-1/2   | 4-15/16 | 2- 3/16 | 11-3/4  | 1.71               |
| 429-420E                | 4X2         | 7-15/32  | 5       | 2-23/32 | 4- 1/16 | 1.28               |
| 429-420FE <sup>2*</sup> | 4X2         | 12-13/16 | 4-15/16 | 2-11/16 | 8-13/16 | 1.64               |
| 429-421FE <sup>2*</sup> | 4X2-1/2     | 11- 3/4  | 4-15/16 | 3- 1/4  | 7- 1/2  | 1.64               |
| 429-422FE <sup>*</sup>  | 4X3         | 8- 5/8   | 4-15/16 | 3-15/16 | 4- 1/8  | 1.22               |
| 429-490FE <sup>*</sup>  | 5X4         | 9- 7/16  | 6- 1/16 | 5       | 4- 3/16 | 1.90               |
| 429-527FE <sup>4*</sup> | 6X1-1/2     | 23-3/16  | 7-1/8   | 2-3/16  | 18-7/16 | 3.70               |
| 429-528FE <sup>2*</sup> | 6X2         | 15- 7/8  | 7- 1/8  | 2-11/16 | 11- 1/4 | 3.51               |