




Coupling - Reducer

(Continued)

Socket x Socket



Part Number	Size	L	M	M1	N	Approx. Wt. (Lbs.)
829-621F ⁺	10X2	21- 1/2	11- 3/4	5- 3/16	14-15/16	16.16
829-623F ⁺	10X3	21- 7/16	11- 3/4	5- 3/16	14-5/16	15.77
829-624F ⁺	10X4	21- 1/8	11- 3/4	5- 3/16	13- 5/8	14.75
829-625F ⁺	10X5	21- 3/16	11- 3/4	6- 5/16	12-15/16	14.90
829-626	10X6	10-19/32	12- 1/32	7-19/32	2-17/32	11.07
829-626F ⁺	10X6	17- 1/2	11- 3/4	7- 1/2	9	16.01
829-628	10X8	10- 5/8	12	9- 3/4	1-17/32	11.29
829-628F ⁺	10X8	13-1/4	11-3/4	9-5/8	3-3/4	11.36
829-663F ⁺	12X3	28-11/16	13-15/16	5-3/16	20-9/16	27.97
829-664F ⁺	12X4	28- 3/8	13-15/16	5- 3/16	19- 7/8	30.99
829-665F ⁺	12X5	28- 7/16	13-15/16	6- 5/16	19- 3/16	28.96
829-666F ⁺	12X6	24- 3/4	13-15/16	7- 1/2	15- 1/4	30.03
829-668	12X8	12- 5/8	14- 7/32	9- 3/4	2- 7/16	17.85
829-668F ⁺	12X8	20- 1/2	13-15/16	9- 5/8	10	26.08
829-670F ⁺	12X10	16- 3/8	13-15/16	11-15/16	4- 7/8	20.57
829-691F ⁺	14X2	30-1/2	15-3/16	5-3/16	22	36.11
829-694F ⁺	14X4	30- 1/8	15- 3/16	5- 3/16	20- 7/8	29.93
829-696F ⁺	14X6	26- 1/2	15- 3/16	7- 1/2	16- 1/4	33.67
829-698F ⁺	14X8	22- 1/4	15- 3/16	9- 5/8	11	31.22
829-700F ⁺	14X10	18- 1/8	15- 3/16	11-15/16	5- 7/8	24.68
829-702F ⁺	14X12	17- 3/4	15- 3/8	14- 1/8	4- 1/2	27.40
829-754F ⁺	16X4	38	17- 3/8	5- 3/16	27- 3/4	50.44
829-756F ⁺	16X6	34- 3/8	17- 3/8	7- 1/2	23- 1/8	57.36
829-758F ⁺	16X8	30- 1/8	17- 3/8	9- 5/8	17- 7/8	53.41
829-760F ⁺	16X10	26	17- 3/8	11-15/16	12- 3/4	47.90
829-762F ⁺	16X12	20- 1/4	17- 3/8	14- 1/8	6	37.66
829-764F ⁺	16X14	21- 1/4	17- 1/2	15- 1/2	5- 1/4	42.89
829-783F ⁺	18X3	47-11/16	19-11/16	5-3/16	36-13/16	95.74
829-784F ⁺	18X4	47- 3/8	19-11/16	5- 3/16	36- 1/8	86.76
829-786F ⁺	18X6	43- 3/4	19-11/16	7- 1/2	31- 1/2	93.96
829-788F ⁺	18X8	39- 1/2	19-11/16	9- 5/8	26- 1/4	89.60
829-790F ⁺	18X10	35- 3/8	19-11/16	11-15/16	21- 1/8	84.51
829-792F ⁺	18X12	29- 5/8	19-11/16	14- 1/8	14- 3/8	68.96
829-794F ⁺	18X14	29- 5/8	19-11/16	15- 1/2	13- 5/8	75.39
829-796F ⁺	18X16	23	19-11/16	17-11/16	6	57.24
829-814F ⁺	20X4	58	21- 7/8	5- 3/16	45- 3/4	128.41
829-816F ⁺	20X6	54- 3/8	21- 7/8	7- 1/2	41- 1/8	131.05
829-818F ⁺	20X8	50- 1/8	21- 7/8	9- 5/8	35- 7/8	140.15
829-820F ⁺	20X10	46	21- 7/8	11-15/16	30- 3/4	137.53
829-822F ⁺	20X12	40- 1/4	21- 7/8	14- 1/8	24	127.28