



Packard C-Frame Motor 208-230 Volts 3000 RPM

Item ID: 21964K

- Direct Replacement for Rheem
- Shaded Pole
- "C" Frame Motor with Centrifugal Switch
- This kit contains one Fasco K628 motor and three Fan Blades each with 10 blades and 1/4" diameter bore, in diameters of 3", 3 1/2" and 4".
- Rotation is determined by viewing the shaft end.

Item Specifications

Speeds	1
Volts	208-230
Amps	0.25
Rotation	CW
RPM	3000
Bearings	Sleeve
Enclosure	Open
Shaft Length (In.)	1 1/2
Stack Size (In.)	3/4
Motor Type	Shaded Pole
Frame	C-Frame
Overload	Automatic
Phase	1
Shaft Diameter (In.)	1/4
Shafts	1
Hertz	60
Shaft Dimension (In.)	1/4 x 1 1/2

This Item Replaces

Fasco	7102-0628
Fasco	7102-2163
Goodman	B19400
ICP	512196411
Keeprite	504015
Keeprite	50415K
Nordyne	RH512196411
Rheem	51-21964-01
Rheem	51-21964-11
Rheem	7102-2163
Rheem	7102-0628
Trane	MOT-3428