

## 52" 3 Blade Fan

 Ceiling mounted • Dry location listed 

### Description:

This ceiling fan includes an LED light source covered by a white opal shade to help extend your day into the evening. You and your family will relax in your peaceful retreat created by the cool breeze coming from the three-blades rotating overhead. The fixture is coated in a nickel finish to complete the handsome design.

### Specifications:

- Painted Nickel (-152)
- Steel Construction
- White Opal Glass
- You and your family will relax in your peaceful retreat created by the cool breeze coming from the three-blades rotating overhead.
- This ceiling fan includes an LED light source covered by a white opal shade to help extend your day into the evening.
- The fixture is coated in a painted nickel finish to complete the handsome design.
- Ideal for any living room, great room, or bedroom.
- Perfect for modern or traditional settings.
- Measures 52-inch width by 15-3/4-inch height.
- Uses two medium base bulbs that are sold separately (9.5w max - LED, halogen, or incandescent).
- Able to be fully dimmable with dimmable bulbs.
- Includes installation instructions and mounting hardware.
- Progress Lighting products are designed for exceptional quality, reliability, and functionality.
- Fully dimmable with dimmable bulbs.
- Canopy 80" of wire supplied
- Meets California Title 24 JA8-2016

### Performance:

Number of Modules	2
Input Power	9.5w per module
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	per module
CCT	3000 K
CRI	80 CRI
Life (hours)	15,000 (L70/TM-21)
Warranty	Limited Lifetime warranty
Labels	UL Dry location listed Meets California Title 24 JA8-2016

## P2553-152WB

### Images:



### Dimensions:

 Diameter: 52"  
 Height: 15-3/4"

 Width: 9.2"  
 Height: 2.87"

**P2553-152WB****Dimming Notes:**

---

P2553 is designed to be compatible with many controls.

The following is a partial list of known compatible dimmer controls.

**Dimming Controls**

---

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.