

# Press Tools



## RP 340 PRESS TOOL

The industry-leading RP 340 press tool has a 4" pipe and tubing capacity and weighs only 6 pounds. It features a 180° rotating swivel barrel, perfect for getting at hard-to-reach connections. An available 18V Advanced Lithium 4 battery helps the RP 340 achieve as much as 400 presses per charge, and it has an industry-leading service interval of 42,000 cycles. An optional AC power adapter can further maximize uptime job site to job site.

- 30% smaller tool increases maneuverability.\*
- 17% lighter tool reduces operator fatigue.\*
- More than 400 presses per charge (using Advanced Lithium 4 Battery).
- Ultimate flexibility with the ability to switch between battery and AC power on the same tool.\*\*
- LED-light for continued operations in no or low-light environments.

\*Versus RP 330-B.  
\*\*AC battery adaptor is not available in Australia.

### SPECIFICATIONS

- Capacity – ½" to 4" for Copper and Stainless Steel, ½" to 2" for PEX, ½" to 4" for Steel (½" to 2" with RP 340, 2 ½" to 4" with RP 340 and Press Booster)
- Head Rotation – 180° barrel/jaw swivel
- Hydraulic Ram Output – 7,200 lbs. (32kN)
- Weight – 8.3 lbs./3.76 kg with Advanced Lithium 2 battery, 9.5 lbs./4.3 kg with AC power adapter
- Operating Temperature Range – 15°F to 122°F (-10°C to 50°C)
- Approximate Cycle Time – 4-5 seconds
- Service Interval – 42,000 cycles
- Compatibility – Uses RIDGID Standard Series pressing jaws and attachments. For use with copper and stainless steel tubing, steel pipe, PEX and cutting soil pipe

Catalog No.	Description	Weight		Std. Pack
		lb.	kg	
43348	RP 340 Battery Press Tool Kit (No Jaws)	19	8.6	1
43353	RP 340 Battery Press Tool Kit w/ProPress Jaws (½"-1")	31	14.1	
43358	RP 340 Battery Press Tool Kit w/ProPress Jaws (½"-2")	51	23.1	
43363	RP 340 Corded Press Tool Kit (No Jaws)	16	7.2	
43368	RP 340 Corded Press Tool Kit w/ProPress Jaws (½"-1")	28	12.7	
43373	RP 340 Corded Press Tool Kit w/ProPress Jaws (½"-2")	48	21.8	
44483	RP 340 Press Tool Only	7.3	3.3	

All Battery Press Tool Kits include RP 340, two 2.0Ah 18V Batteries, charger and carrying case.  
All Corded Press Tool Kits include RP 340, 120V AC Power Adapter and carrying case.

### Accessories

Catalog No.	Description	Weight		Std. Pack
		lb.	kg	
43378	RP 340 Press Tool Carrying Case	8	3.6	1
44693	18V Advanced Lithium 2.0Ah Battery	1	0.5	
44698	18V Advanced Lithium 4.0Ah Battery	1.5	0.7	
43458	Advanced Lithium Battery Charger (N. America)	1.8	0.8	
44798	Charger Replacement Cord (N. America)	0.3	0.1	
44468	120V AC Power Adapter	1	0.4	
44848	Set of (1) 2.0Ah Battery & (1) 120V Charger	2.8	1.3	
44853	Set of (2) 2.0Ah Batteries & (1) 120V Charger	3.8	1.7	

### Standard Equipment

Catalog No. Model No.	Description	43348 RP 340-B	43353 RP 340-B	43358 RP 340-B	43363 RP 340-C	43368 RP 340-C	43373 RP 340-C
76652	½" Jaw for ProPress		•	•		•	•
76657	¾" Jaw for ProPress		•	•		•	•
76662	1" Jaw for ProPress		•	•		•	•
76667	1 ¼" Jaw for ProPress			•			•
76672	1 ½" Jaw for ProPress			•			•
76677	2" Jaw for ProPress			•			•
44693	18V Advanced Lithium 2Ah Battery	•	•	•			
43458	Advanced Lithium Battery Charger (N America)	•	•	•			
44468	120V AC Power Adapter				•	•	•
43378	Carrying Case	•	•	•	•	•	•